

UT-131D

Multimetro palmare tascabile autorange per letture di tensione e corrente in continua e alternata, adatto sia per uso da laboratorio che installatori e elettricisti.

Funzioni Speciali:

- Prova diodi e Buzzer Di Continuità
- Autospegnimento
- Indicatore batteria scarica
- Display Retroilluminato

Specifications	Range	UT131D
DC voltage (V)	200mV~250V	±(0.5%+2)
AC voltage (V)	200V~250V	±(1.2%+10)
DC current (A)	2000μA~10A	±(1%+2)
Resistance (Ω)	200Ω~200MΩ	±(0.8%+2)
Features		
Display count		2000
Auto power off/Auto backlight off		√
Diode test/Continuity buzzer		√
Drop test		2m
Test probe holder		√
Range selection		Manual
NCV		√
General Characteristics		
Power	1.5V battery (R03) x 2	
Display	66mm x 51mm	
Product net weight	300g	
Product color	Red and grey	
Product size (W x H x D)	131mm x 95mm x 58mm	
Standard accessories	Test lead, manual	
Standard individual packing	Gift box, English manual	
Standard quantity per carton	60pcs	
Standard carton measurement	640mm x 310mm x 350mm	
Standard carton gross weight	19.4kg	